

KC091

Addition Pen

Addition pen for plates. This pen is available with broad tip.

Broad tip: case of 3 pens **Art. code** R2Q2Q

Working instructions

Correction on a developed plate before printing

- Remove any gum of the area which needs to be corrected with a wet cotton path or wet sponge.
- Wipe the area complete dry.
- Perform your correction by writing with the pen (only once - not several times over the same area).
- Re-gum the plate and wipe the plate dry before printing.
- After correction, always put the cap on the pen.

On press correction

- Remove the ink from the plate with the dedicated plate cleaner.
- Be sure that all ink is removed.
- Make the correction area complete dry.
- Perform your correction by writing with the pen (only once - not several times over the same area).
- After correction, always put the cap on the pen.

Safety

Read MSDS before using this product.

Storage

- Store at room temperatures in a dry, well ventilated area.
- Keep away from heat and direct sunlight.
- Keep the pen closed.
- Shelf life: 24 months from date of manufacture

Waste

Collect if possible, send to authorized disposal centres, in accordance with local and national regulations.

Agfa Graphics plate compatibility

Digital plate technology									
Thermal									
:Azura TS	:Amigo TS	:Thermostar P970	:Thermostar P970 baked	:Energy Xtra	:Energy Xtra baked	:Energy Elite	:Energy Elite baked	:Energy Elite Pro	:Energy Elite Pro baked
✓	✓	✓	n/a	✓	n/a	✓	n/a	✓	n/a

Visible light						
:Aspire	:Aspire baked	:Azura-Vi	:N91v	:N94v	:N94-VCF	:Lithostar Ultra
✓	n/a	✓	✓	✓	✓	✓

CtCP plate technology			Analogue plate technology		
:Aluva P	:Aluva P baked	:Aluva N	:Meridian P55	:Meridian P55 baked	:Zenith N555
✓	n/a	✓	✓	n/a	✓