

# KN250

## Deletion Fluid

Correction fluid for negative analogue plates

6 x 0.1L bottle **Art. code** P5Y CZ

### Working instructions

#### Correction on a developed plate before printing

- Remove the image with the correction fluid.
- Immediately after correction, remove with a wet cotton path or wet sponge the correction fluid residue left on the plate. Be careful that you don't wipe the correction fluid residue in the image area.
- Rinse the corrected area several times with a wet cotton path, to be sure that all residues are removed.
- Wipe the plate dry and re-gum the plate with the gum in use (manual or in rinse-gum of processor)
- Wipe the plate dry after re-gumming.
- After correction, always put the cap on the bottle

#### On press correction

- Remove the ink from the plate with the dedicated plate cleaner.
- Be sure that all ink is removed.
- Make the correction area complete dry.
- Remove the image with the correction fluid.
- Immediately after correction, remove with a wet cotton path or wet sponge the correction fluid residue left on the plate. Be careful that you don't wipe the correction fluid residue in the image area.
- Rinse the corrected area several times with a wet cotton path, to be sure that all residues are removed.
- Wipe the plate dry.
- After correction, always put the cap on the bottle.

### Safety

Read MSDS before using this product.

### Storage

- Store at room temperatures in a dry, well ventilated area.
- Keep away from heat and direct sunlight.
- Keep the bottle closed.
- Shelf life: 24 months from date of manufacture.

### Waste

Collect if possible, send to authorized disposal centres, in accordance with local and national regulations.

### Agfa Graphics plate compatibility

Digital plate technology									
Thermal									
:Azura TS	:Amigo TS	:Thermostar P970	:Thermostar P970 baked	:Energy Xtra	:Energy Xtra baked	:Energy Elite	:Energy Elite baked	:Energy Elite Pro	:Energy Elite Pro baked
✗	✗	✗	✗	✗	✗	✗	✗	✗	✗

  

Visible light						
:Aspire	:Aspire baked	:Azura-Vi	:N91v	:N94v	:N94-VCF	:Lithostar Ultra
✗	✗	✗	✗	✗	✗	✗

  

CtCP plate technology			Analogue plate technology		
:Aluva P	:Aluva P baked	:Aluva N	:Meridian P55	:Meridian P55 baked	:Zenith N555
✗	✗	✓	✗	✗	✓